

Product Summary


V_{DS} (V)	$R_{DS(on),max}$ (mΩ)	I_D (A)
40	6.8 @ $V_{GS} = 10V$	59 ⁽¹⁾

Features

- Low $R_{DS(on)}$ trench technology
- Low thermal impedance
- Fast switching speed
- 100% avalanche tested

Application


- DC/DC conversion
- Power switch
- Motor drives
- Li- Battery Protection




PDFN5060

NOTE:
 LOGO - GS
 GMXXXXX- Part number code
 F - Fab location code
 A - Assembly location code
 Y - Year code
 WW - Week code
 L&T - Assembly lot code

PDFN5060



Equivalent circuit



Absolute maximum rating@25°C

Parameter	Symbol	Limit	Unit
Drain-source voltage	V_{DS}	40	V
Gate-source voltage	V_{GS}	±20	
Continuous drain current	I_D	59	A
	I_D	37	
Pulsed drain current ⁽²⁾	$I_{D,pulse}$	232	
Avalanche energy, single pulse ⁽³⁾	E_{AS}	53	mJ
Power dissipation	P_D	39	W
	P_D	16	
Operating junction and storage temperature range	T_J, T_{stg}	-55 to 150	°C

Thermal Characteristic

Parameter	Symbol	Max.	Unit
Thermal resistance, junction-to-case	$R_{\theta JC}$	3.2	°C/W
Thermal resistance, junction-to-ambient ⁽⁴⁾	$R_{\theta JA}$	60	

Electrical Characteristics (T_J=25°C unless otherwise noted)

Parameter	Symbol	Test conditions	Min.	Typ.	Max.	Unit
Static parameter						
Drain to source breakdown voltage	V _{(BR)DSS}	V _{GS} = 0, I _D = 250 μA	40			V
Gate-source threshold voltage	V _{GS(th)}	V _{DS} = V _{GS} , I _D = 250 μA	1.2	1.6	2.5	V
Gate-body leakage	I _{GSS}	V _{DS} = 0 V, V _{GS} = ±20 V			±100	nA
Zero gate voltage drain current	I _{DSS}	V _{DS} = 40 V, V _{GS} = 0 V			1	μA
Drain-source on-resistance	R _{DS(on)}	V _{GS} = 10 V, I _D = 20 A		5.6	6.8	mΩ
		V _{GS} = 4.5 V, I _D = 15 A		8.0	9.9	
Forward transconductance ⁽⁵⁾	g _{fs}	V _{DS} = 5 V, I _D = 30 A		17		S
Gate resistance	R _g	f = 1 MHz		6.2		Ω
Dynamic ⁽⁵⁾						
Total gate charge V _{GS} = 10V	Q _g	V _{DS} = 20 V, I _D = 20 A, V _{GS} = 10 V		9.0		nC
Total gate charge V _{GS} = 4.5V	Q _g			3.9		
Gate-source charge	Q _{gs}			1.8		
Gate-drain charge	Q _{gd}			0.8		
Turn-on delay time	t _{d(on)}	V _{DS} = 20 V, I _D = 20 A, V _{GS} = 10 V, R _{GEN} = 3 Ω		2.0		ns
Rise time	t _r			2.4		
Turn-off delay time	t _{d(off)}			14		
Fall time	t _f			7.9		
Input capacitance	C _{iss}	V _{DS} = 20 V, V _{GS} = 0 V, f = 1 MHz		570		pF
Output capacitance	C _{oss}			359		
Reverse transfer capacitance	C _{rss}			20		
Reverse Diode Characteristics ⁽⁵⁾						
Diode forward voltage	V _{SD}	V _{GS} = 0 V, I _F = 2 A		0.74	1.2	V
Reverse recovery time	t _{rr}	I _F = 20 A, di/dt = 100 A/μs		27		ns
Reverse recovery charge	Q _{rr}			7.8		nC

Notes

- (1) Limited by maximum junction temperature.
- (2) Pulse width limited by maximum junction temperature.
- (3) V_{DS} = 20 V, V_{GS} = 10 V, L = 1.0 mH.
- (4) Device mounted on FR-4 substrate PC board with 2oz copper in 1inch square cooling area.
- (5) Guaranteed by design, not subject to production testing.

Typical Performance Characteristics




Figure 1: Output Characteristics




Figure 2: Transfer Characteristics




Figure 3: On-Resistance vs. Gate-Source Voltage




Figure 4: On-Resistance vs. Gate-Source Voltage




Figure 5: On-Resistance vs. Junction Temperature




Figure 6: Source-Drain Diode Forward Voltage

Typical Performance Characteristics




Figure 7: Gate Threshold Variation vs. Junction Temperature




Figure 8: Gate Charge Characteristics




Figure 9: Capacitance Characteristics




Figure 10: Power Derating




Figure 11: Current Derating




Figure 12: Safe Operating Area

Typical Performance Characteristics








Figure 13: Normalized Maximum Transient Thermal Impedance

Test Circuit & Waveform



Gate Charge Test Circuit & Waveform





Resistive Switching Test Circuit & Waveforms




Unclamped Inductive Switching (UIS) Test Circuit & Waveforms



Diode Recovery Test Circuit & Waveforms



Outline Drawing PDFN5060


Dim	Millimeters		
	Min	Nom	Max
A	0.900	1.000	1.100
A1	0.000	---	0.050
b	0.246	0.254	0.312
c	0.310	0.410	0.510
d	1.27BSC		
D	4.950	5.050	5.150
D1	4.000	4.100	4.200
D2	---	---	0.125
e	0.62BSC		
E	5.500	5.600	5.700
E1	6.050	6.150	6.250
E2	3.425	3.525	3.625
E3	0.150	0.250	0.350
E4	0.175	0.275	0.375
F	---	---	0.100
L	0.500	0.600	0.700
L1	0.600	0.700	0.800

Important Notice

The information given in this document shall be for illustrative purposes only and shall in no event be regarded as a guarantee of conditions or characteristics. Gostone reserves the right to change any information herein. With respect to any examples, hints or any typical values stated herein and/or any information regarding the application of the product, Gostone or its affiliates hereby make no representation or warranty of any kind, expressed or implied, as to any information provided hereunder, including without limitation as to the accuracy, completeness or non-infringement of intellectual property rights of any third party, and they assume no liability for the consequences of use of such information. In addition, any information given in this document is subject to customer's compliance with its obligations stated herein and any applicable legal requirements, norms and standards concerning customer's products and any use of the product of Gostone in customer's applications. The information contained herein is exclusively intended for technically trained staff. No license is granted by implication under any patent right, copyright, mask work right, or other intellectual property right. It is customer's sole responsibility to evaluate the suitability of the product for the intended application and the completeness of the product information given herein with respect to such application. In no event shall Gostone or its affiliates be liable to any party for any direct, indirect, special, punitive, incidental or consequential damages of any nature whatsoever, including but not limited to loss of profits and loss of goodwill, whether or not such damages are based on tort or negligence, warranty, breach of contract or any other legal theory. In addition, any recipient of this document and the relevant products samples may not alter, decompile, disassemble, reverse engineer, or otherwise modify any information/samples received hereunder. Any intellectual property rights arising from the reverse engineering of Gostone's products shall belong to Gostone.